

REMOTE CONTROL Code for EIP-3500

2005/11/27


No.	Key Description	Binary															HEX				
		System Code					Data Code										Judgement of frame		System Code	Data Code	Judgement of frame
		C1	C2	C3	C4	C5	C6	C7	C8	C9	C10	C11	C12	C13	C14	C15					
1	On-Standby	1	0	1	1	0	0	1	1	0	1	0	0	0	1	0	0	D	1	6	1
2	Zoom (+)	1	0	1	1	0	0	0	0	1	0	1	0	1	1	0	0	D	A	8	1
3	Focus (+)	1	0	1	1	0	0	0	1	0	0	1	1	1	1	0	0	D	E	4	1
4	Auto Focus	1	0	1	1	0	1	0	1	1	1	0	1	1	1	0	0	D	D	D	1
5	Zoom (-)	1	0	1	1	0	1	0	0	1	0	1	0	1	1	0	0	D	A	9	1
6	Focus (-)	1	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0	D	E	5	1
7	Iris	1	0	1	1	0	0	1	0	1	0	1	0	1	1	0	0	D	A	A	1
8	Keystone	1	0	1	1	0	1	1	0	1	0	0	0	1	1	0	0	D	8	A	1
9	Menu	1	0	1	1	0	0	0	1	0	0	0	1	1	1	0	0	D	C	4	1
10	Enlarge (+)	1	0	1	1	0	1	0	1	1	0	1	1	0	1	0	0	D	6	D	1
11	Freeze	1	0	1	1	0	1	0	1	1	0	0	0	1	1	0	0	D	8	D	1
12	Vol (+)	1	0	1	1	0	0	0	1	0	1	0	0	0	1	0	0	D	1	4	1
13	Enlarge (-)	1	0	1	1	0	1	0	1	1	0	1	0	1	1	0	0	D	A	D	1
14	AV Mute	1	0	1	1	0	1	0	0	1	0	1	1	0	1	0	0	D	6	9	1
15	Vol (-)	1	0	1	1	0	1	0	1	0	1	0	0	0	1	0	0	D	1	5	1
16	RGB1 (Input1)	1	0	1	1	0	1	0	1	0	1	1	0	0	1	0	0	D	3	5	1
17	RGB2 (Input2)	1	0	1	1	0	0	1	1	0	1	1	0	0	1	0	0	D	3	6	1
18	Picture Mode	1	0	1	1	0	1	0	0	1	1	1	0	0	1	0	0	D	3	9	1
19	Video1 (Input3)	1	0	1	1	0	0	1	0	0	1	1	0	0	1	0	0	D	3	2	1
20	Video2 (Input4)	1	0	1	1	0	1	1	0	0	1	1	0	0	1	0	0	D	3	3	1
21	Auto Sync	1	0	1	1	0	0	1	0	1	1	1	1	1	1	0	0	D	F	A	1
22	Resize	1	0	1	1	0	0	1	1	1	1	0	1	0	1	0	0	D	5	E	1

remote controller relevant document


1. format of Sharp's 15 bit for remote controller

Remote controller outputs the party of surface and reverse of 15 bit as one frame.

1-1. frame cycle



1-2. data



1-3. carrier

