

### EIKI: LC-WB100 / IR Command List

- Transmission format of LCD projector operation key  
: NEC Format (single command / command pipelining mode)
- Custom Code + Custom Code  
: 2 patterns as below  
33h+00h(Default;code1), 33h+11h(code2)

| Key No. | Data Code (HEX) | Function     |
|---------|-----------------|--------------|
| 1       | 38              | COMPUTER 1   |
| 2       | 39              | COMPUTER 2   |
| 3       | 00              | ON-OFF       |
| 4       | 3D              | VIDEO        |
| 5       | 3E              | S-VIDEO      |
| 6       | 83              | COMPONENT    |
| 7       | 37              | HDMI         |
| 8       | 1C              | MENU         |
| 9       | 5B              | KEystone     |
| 10      | 8C              | CURSOR UP    |
| 11      | 1E              | CURSOR LEFT  |
| 12      | 1D              | CURSOR RIGHT |
| 13      | 8D              | CURSOR DOWN  |
| 14      | 0F              | SELECT       |
| 15      | 01              | D.ZOOM +     |
| 16      | 82              | SCREEN       |
| 17      | 17              | AUTO SET     |
| 18      | 0C              | IMAGE        |
| 19      | 02              | D.ZOOM -     |
| 20      | 07              | PIP          |
| 21      | 43              | FREEZE       |
| 22      | 8A              | P-TIMER      |
| 23      | 09              | VOLUME +     |
| 24      | 8B              | NO SHOW      |
| 25      | 0B              | MUTE         |
| 26      | 0A              | VOLUME -     |
| 27      | 16              | INFORMATION  |
| 28      | 18              | LAMP CONTROL |