

G035 RS232 command table:

Rs232 Default Setting:

Baud rate : 19200

Data : 8 Bit

Parity : none

Stop : 1 bit

Flow control : none

Command No	Command Description	Command Code	Command Value	Response
1	Power On	~poweron	N/A	
2	Power Off	~poweroff	N/A	
3	R-sync	~rsync	N/A	
4	Mute	~mute	N/A	
5	Mute Off	~muteoff	N/A	
6	Get Mute State	~rmute	N/A	0:off 1:on
7	Freeze	~freeze	N/A	
8	Freeze Off	~freezeoff	N/A	
9	Blank	~blank	N/A	
10	Blank off	~blankoff	N/A	
11	Get Blank State	~rblank	N/A	0:off 1:on
12	Color Mode	~colormode	0:Bright 1:PC 2:Movie 3:Game 4:User	
13	Color Mode Read	~rcolormode	N/A	0:Bright 1:PC 2:Movie 3:Game 4:User
14	Aspect Ratio	~aspectratio	1: Auto 2: 4:3 3: 16:9 4: 16:10	

15	Aspect Ratio Read	~rapectratio	N/A	1: Auto 2: 4:3 3: 16:9 4: 16:10
16	Source-HDMI	~hdmi	N/A	
17	Source-VGA-1	~vgaa	N/A	
18	Source-VGA-2	~vgab	N/A	
19	Source-S-Video	~svideo	N/A	
20	Source-Composite	~composite	N/A	
21	Current Source	~rsource	N/A	0: VGA-1 1: VGA-2 2: COMPOSITE 3: S-video 4: HDMI
22	V. Keystone Read	~rkeystone	N/A	15 ~ -15
23	Factory Reset	~factoryreset	N/A	
24	Lamp-Hours	~rlamphour	N/A	
25	Firmware Version	~rfirmwarev	N/A	AXX
26	Ceiling Mount	~ceiling	0: Front 1: Front Ceiling 2: Rear 3: Rear Ceiling	
27	Ceiling Mount Read	~rceiling	N/A	0: Front 1: Front Ceiling 2: Rear 3: Rear Ceiling
28	Brightness Write	~brightness	0 ~ 100	
29	Brightness Read	~rbrightness	N/A	0~100
30	Contrast Write	~contrast	0 ~ 100	
31	Contrast Read	~rcontrast	N/A	0 ~100

32	Current Language Write	~clanguage	1 ~ 17	1: English 2: German 3: French 4: Italian 5: Spanish 6: Polish 7: Swedish 8: Dutch 9: Iberian Portuguese 10: Japanese 11: T_Chinese 12: S_Chinese 13: Korean 14: Russian 15: Arabic 16: Dansk 17: Turkish
33	Current Language Read	~rclanguage	N/A	1 ~ 17
34	Volume Write	~volume	0 ~ 32	
35	Volume Read	~rvolume		0 ~ 32
34	Microphone Volume Write	~mvolume	0 ~ 32	
35	Microphone Volume Read	~rmvolume		0 ~ 32
37	Auto Power Off	~autopoweroff	0 ~ 120	
38	Read Auto Power Off	~rautopoweroff	N/A	0 ~ 120
39	Operating Hours	~rophours	N/A	Hours
40	System Status	~rsystem	N/A	0: Standby 1: Warm Up 2: Lamp On 3: Cooling