

REMOTE CONTROL Code for EIP-250/2600

2008/11/7

No.	Key Description	Binary															HEX						
		System Code					Data Code										Judgement of frame		System Code		Data Code		Judgement of frame
		C1	C2	C3	C4	C5	C6	C7	C8	C9	C10	C11	C12	C13	C14	C15							
30	Standby	1	0	1	1	0	0	1	1	0	1	0	0	1	1	0	0	D	9	6	1		
22	Power ON	1	0	1	1	0	0	1	1	0	1	0	1	0	1	0	1	D	5	6	1		
6	Computer	1	0	1	1	0	1	0	1	0	1	1	0	0	1	0	1	D	3	5	1		
25	S-Video	1	0	1	1	0	0	1	0	0	1	1	0	0	1	0	1	D	3	2	1		
33	Video	1	0	1	1	0	1	1	0	0	1	1	0	0	1	0	1	D	3	3	1		
34	Break Timer	1	0	1	1	0	0	0	1	0	1	1	0	1	1	0	1	D	B	4	1		
35	Freeze	1	0	1	1	0	1	0	1	1	0	0	0	1	1	0	1	D	8	D	1		
37	AV Mute	1	0	1	1	0	1	0	0	1	0	1	1	0	1	0	1	D	6	9	1		
7	Magnify (+)	1	0	1	1	0	1	0	1	1	0	1	1	0	1	0	1	D	6	D	1		
15	Back	1	0	1	1	0	1	1	1	1	0	1	0	1	1	0	1	D	A	F	1		
23	Vol (+)	0	0	1	1	0	0	0	1	0	1	0	0	0	1	0	1	D	1	4	1		
29	Magnify (-)	1	0	1	1	0	1	0	1	1	0	1	0	1	1	0	1	D	A	D	1		
13	Forward	1	0	1	1	0	0	1	1	1	0	1	0	1	1	0	1	D	A	E	1		
21	Vol (-)	1	0	1	1	0	1	0	1	0	1	0	0	0	1	0	1	D	1	5	1		
27	Pointer	1	0	1	1	0	1	0	0	0	1	0	1	0	1	0	1	D	5	1	1		
28	Spot	1	0	1	1	0	1	1	0	1	1	1	1	1	1	0	1	D	F	B	1		
8	Cursol Up	Code is not opened by R/C manufacturer																					
16	Cursol Left	Code is not opened by R/C manufacturer																					
24	Cursol Right	Code is not opened by R/C manufacturer																					
32	Cursol Down	Code is not opened by R/C manufacturer																					
36	Enter	1	0	1	1	0	1	1	1	0	1	0	1	0	1	0	1	D	5	7	1		
40	L-click	Code is not opened by R/C manufacturer																					
48	R-click	Code is not opened by R/C manufacturer																					
9	Keystone	1	0	1	1	0	1	1	0	1	0	0	0	1	1	0	1	D	8	B	1		
12	Picture Mode	1	0	1	1	0	1	0	0	1	1	1	0	0	1	0	1	D	3	9	1		
10	Menu/Help	1	0	1	1	0	0	0	1	0	0	0	1	1	1	0	1	D	C	4	1		
17	Auto Sync	1	0	1	1	0	0	1	0	1	1	1	1	1	1	0	1	D	F	A	1		
20	Eco+Quit	1	0	1	1	0	1	0	0	1	1	0	0	0	1	0	1	D	1	9	1		
18	Resize	1	0	1	1	0	0	1	1	1	1	0	1	0	1	0	1	D	5	E	1		
38	DVI	1	0	1	1	0	0	1	1	0	1	1	0	0	1	0	1	D	3	6	1		

EIP-2600 only