

2007/11/14

LC-XB41 (SANYO : PLC-XU101) IR Command List

- Transmission format of LCD projector operation key
: NEC Format (single command / command pipelining mode)
- Custom Code + Custom Code
: 2 patterns as below
33h+00h(Default;code1), 33h+11h(code2)

Key No.	Data Code (HEX)	Function
1	38	COMPUTER
2	05	VIDEO
3	00	ON-OFF
4	1C	MENU
5	5B	KEYSTONE
6	8C	CURSOR UP
7	1E	CURSOR LEFT/VOLUME -
8	1D	CURSOR RIGHT/VOLUME +
9	8D	CURSOR DOWN
10	0F	SELECT
11	01	D.ZOOM +
12	89	AUTO PC
13	0C	IMAGE
14	02	D.ZOOM -
15	43	FREEZE
16	8A	P-TIMER
17	8B	NO SHOW
18	0B	MUTE
19	18	LAMP CONTROL