


IR Command Code Protocol For LC-XDP3500

IR Protocol

-IR Remote Control Specification

Items	Specification
Projector Transceivers	The projector shall have IR transceivers on the front and rear of the unit.
Working Frequency	38k Hz or 57k Hz
Effective Range and Distance	7 meters / Horizontal $\pm 15^\circ$ Vertical $\pm 15^\circ$

-Command Code List

Custom Code			Remote Control ID
0x6A			
Data Code			
Item	Value	Command Description	
Code1	0x00	Power	
Code2	0x11	Input	
Code3	0x0b	Menu Right ,Volume + (Up)	
Code4	0x0f	Menu Left , Volume - (down)	
Code5	0x14	Menu Up	
Code6	0x19	Menu Down	
Code7	0x27	Menu	
Code8		Laser Pointer	
Code9	0x13	Mute	
Code14	0x1f	Auto	
Code16	0x23	Blank	