

RS232C Command List(Basic)

Code	Description	LC-X5
1. Control Command		
C00	Power On	Yes
C01	Compulsory Power Off	Yes
C02	Power Off	-
C05	Input1 Mode Set	Yes
C06	Input2 Mode Set	Yes
C07	Input3 Mode Set	Yes
C08	Input4 Mode Set	
C09	Volume +	Yes
C0A	Volume -	Yes
C0B	Sound Mute On	Yes
C0C	Sound Mute Off	Yes
C0D	No Show On	Yes
C0E	No Show Off	Yes
C0F	Av Regular Size 4:3	Yes
C10	Av Wide Size 16:9	Yes
C1C	Menu On	Yes
C1D	Menu Off	Yes
C1E	Display Clear	Yes
C1F	Normal	-
C20	Brightness Up	
C21	Brightness Down	
C22	Input1 Digital	extended commands are available for these
C23	Input2 S-Video	
C24	Input3 S-Video	
C25	Input2 Component	
C26	Input3 Component	
C27	Image	Yes
C28	On Start On	
C29	On Start Off	
C2A	Power Management On	
C2B	Power Management Off	
C2C	Video Zoom	
C2D	Video Wide Zoom	
C30	D.Zoom+	Yes
C31	D.Zoom-	Yes
C3A	Pointer Right	Yes
C3B	Pointer Left	Yes
C3C	Pointier Up	Yes
C3D	Pointier Down	Yes
C3E	Mupo Rear Sw	-
C3F	Select	Yes
C43	Freeze On	Yes
C44	Freeze Off	Yes
C46	Zoom Down	Yes
C47	Zoom Up	Yes
C4A	Focus Down	Yes
C4B	Focus Up	Yes
C4F	Cursor	-
C59	Mci Page Up	
C5A	Mci Page Down	
C5D	Lens Shift Up	Yes
C5E	Lens Shift Down	Yes
C5F	Lens Shift Left	-
C60	Lens Shift Right	-
C61	Auto Grayscale On	
C62	Auto Grayscale Off	
C63	Auto Fleshtone On	
C64	Auto Fleshtone Off	
C70	Full Lamp(4Lamp) Mode	Full Mode (2)
C71	Half Lamp(2Lamp) 1-4 Mode	Half-1
C72	Half Lamp(1Lamp) 2-3 Mode	Half-2
C80	Select Zoom Mode	
C87	Select Focus Mode	
C88	Select Lens Shift Mode	
C89	Auto Pc Adj.	Yes
C8A	Presentation Timer	Yes
C8E	Keystone +	Yes
C8F	Keystone -	Yes
CDB		

RS232C Command List(Basic)

Code	Description	LC-X5
2. Read Command and Status		
CR0	Status Read	Yes
00	Power On	Yes
80	Stand By	Yes
40	Processing Count Down	Yes
20	Processing Cooling Down	Yes
10	Power Fail	Yes
28	Processing Cooling Down Due To Abnormal Temperature	Yes
08	Abnormal Temperature	Yes
88	Stand By After Cooling Down Due To Abnormal Temperature	Yes
02	Reject Key Input	Yes
24	Processing Power Save And Cooling Down	Yes
04	Stand By After Cooling Down Due To Power Save	Yes
21	During Cooling Down After All Lamps Distinguished	Yes
81	Standby After The Above	Yes
CR1	Input Mode Read	Yes
0	Input1	
1	Input1	Yes
2	Input2	Yes
3	Input3	Yes
4	Input4	-
CR3	Lamp Time Read	Yes
****	4-Digit Number (Hour)	Yes
CR4	Setting Read	Yes
11	Normal	Yes
10	Top/Bottom Reverse	Yes
01	Left/Right Reverse	Yes
00	T/B & L/R Reverse	Yes
CR6	Temp Read	Yes
*.**	: Space, *:A Digit Number	Yes

Example

31.5 35.2 : a temperature of 31.5° & 35.2°

-05.5_-01.2_ : a temperature of -5.5° & -1.2°

E00.0 35.2 : Error and a temperature of 35.2°

CR7	Lamp Mode Read	Yes
00	All Off	Yes
01	No.1:On, No.2,3,4:Off	Yes
02	No.2:On, No.1,3,4:Off	Yes
04	No.3:On, No.1,2,4:Off	
08	No.4:On, No.1,2,3:Off	
03	No.1,2:On, No.3,4:Off	
05	No.1,3:On, No.2,4:Off	
09	No.1,4:On, No.2,3:Off	
06	No.2,3:On, No.1,4:Off	
0A	No.2,4:On, No.1,3:Off	
0C	No.3,4:On, No.1,2:Off	
07	No.1,2,3:On, No.4:Off	
0B	No.1,2,4:On, No.3:Off	
0D	No.1,3,4:On, No.2:Off	
0E	No.2,3,4:On, No.1:Off	
0F	All On	Yes
10	All Off	Yes
11	No.1:On, No.2,3,4:Off	Yes
18	No.4:On, No.1,2,3:Off	
19	No.1,4:On, No.2,3:Off	
20	All Off	Yes
22	No.2:On, No.1,3,4:Off	Yes
24	No.3:On, No.1,2,4:Off	
26	No.2,3:On, No.1,4:Off	
CR9	Pc Type Read	Yes
Stand by	Stand By	Yes
AV Mode	Video Mode	Yes
*****	Pc System (Ex. "Xga1")	Yes
Go PC a	Format Not Listed	Yes
No signa	No Signal	Yes
CRA	Status 2 Read	Yes
00	Video & Audio Mute Off	Yes
01	Video Mute On	Yes
02	Audio Mute On	Yes
03	Video & Audio Mute On	Yes

RS232C Command List(Basic)

Code	Description	LC-X5
------	-------------	-------