

V2000 RC Command List

IR command table

| Key Name | Format | Data code |
|----------|--------|-----------|
| POWER | SANYO | 17 |
| HDMI 1 | SANYO | 1F |
| VGA | SANYO | 1B |
| HDMI2 | SANYO | 25 |
| DVI | SANYO | 1E |
| HDMI3 | SANYO | 0A |
| HDMI4 | SANYO | 1A |
| PATTERN | SANYO | 14 |
| INPUT | SANYO | 40 |
| AUTO | SANYO | 0F |
| MENU | SANYO | 00 |
| UP | SANYO | 18 |
| DOWN | SANYO | 09 |
| LEFT | SANYO | 19 |
| RIGHT | SANYO | 08 |
| OK | SANYO | 07 |
| FOCUS | SANYO | 05 |
| SHIFT | SANYO | 20 |
| ZOOM | SANYO | 04 |
| BLANK | SANYO | 15 |
| FREEZE | SANYO | 13 |
| SCREEN | SANYO | 1C |
| IMAGE | SANYO | 41 |
| KEystone | SANYO | 03 |
| TIMER | SANYO | 42 |
| INFO. | SANYO | 02 |
| DZOOM + | SANYO | 1D |
| DZOOM - | SANYO | 0E |

| ID | Custom Code |
|----|-------------|
| 0 | 0135H |
| 1 | 013EH |
| 2 | 013DH |
| 3 | 013CH |
| 4 | 013BH |
| 5 | 013AH |
| 6 | 0139H |
| 7 | 0138H |
| 8 | 0137H |
| 9 | 0136H |

